

Kramer 4x4A 4x1:4 Stereo Audio Switcher

DESCRIPTION

- The 4x4A is a high-performance switcher for stereo audio signals. It switches any one of four input signals simultaneously to four identical outputs.
 - S/N Ratio - 90dB.
 - Level (Gain) Control.
 - Compact Kramer TOOLS™ - 3 units can be rack mounted side-by-side in a 1U rack space with the optional RK-3T rack adapter.

Rack Adapters: 19" (1U): RK-3T

SPECIFICATIONS

INPUTS:	4 unbalanced stereo audio, 1Vpp/33kohm on 3.5mm mini jacks.
OUTPUTS:	4 unbalanced stereo audio, 1Vpp/220ohm typical on 3.5mm mini jacks.
MAX OUTPUT LEVEL:	5.2Vpp (+7dBu).
AUDIO BANDWIDTH (-3dB):	100kHz.
S/N RATIO:	90dB.
CROSSTALK:	-79dB @1kHz.
THD @1kHz:	0.018%.
2nd HARMONIC:	0.002%.
POWER SOURCE:	12V DC, 20mA.
DIMENSIONS:	12cm x 7.5cm x 2.5cm (4.7" x 2.95" x 0.98") W, D, H.
WEIGHT:	0.28kg (0.62lbs) approx.
ACCESSORIES:	Power supply, mounting bracket.
OPTIONS:	RK-3T 19" rack adapter.