

Kramer VA-1VGAN VGA Video EDID Emulator

DESCRIPTION

The VA-1VGAN is an EDID emulator for computer graphics video signals. The unit can capture an EDID setting in non-volatile memory from the output allowing convenient and reliable connection to the source.

- Input - 15-pin HD.
- Output - 15-pin HD.
- Bandwidth - 1.8GHz.
- Control - Capture button.
- Ultra-Compact Pico TOOLS™ - 4 units can be rack mounted side-by-side in a 1U rack space with the optional RK-4PT rack adapter.

This product replaces the VA-1VGA

SPECIFICATIONS

INPUT:	1 XGA input on a 15-pin HD connector.
OUTPUT:	1 XGA output on a 15-pin HD connector.
MAX. OUTPUT LEVEL:	>2Vpp.
BANDWIDTH (-3dB):	1.8GHz.
DIFF. GAIN:	0.02%.
DIFF. PHASE:	0.02Deg.
K-FACTOR:	<0.05%.
S/N RATIO:	74dB @5MHz (unweighted: 66dB).
CONTROLS:	Push button for EDID monitor information storage.
COUPLING:	DC, direct wiring between input and output.
POWER SOURCE:	5V DC, 20mA.
DIMENSIONS:	6.2cm x 6.2cm x 2.4cm (2.4" x 2.4" x 0.9") W, D, H.
WEIGHT:	0.15kg (0.33lbs) approx.
ACCESSORIES:	Power supply.
OPTIONS:	RK-4PT 19" rack adapter.