

TASCAM DP-008EX Digital 8-Track Recorder with Built-In Microphones

Digital 8-Track Recorder with Built-In Microphones

Features

- Eight mono tracks
- CD-quality recording (16bit/44.1kHz)
- Two tracks simultaneous recording/ eight tracks simultaneous playback
- Dedicated stereo master track available
- Record to SD/SDHC card (Up to 32GB)
- 2 Built-in omni-directional condenser microphones
- Microphone sensitivity can be selected from 2-positions (Low/High)
- Two TS 1/4" or XLR mic/line inputs
- INPUT A can connect high-impedance instrument directly (Like an electric-guitar)
- Phantom power supply
- Independent LEVEL/PAN/Reverb SEND knobs for each track
- Two RCA unbalanced line inputs
- 20mW/ch headphone output
- Footswitch ready with polarity switching (Notice: can't use RC-3F)
- 128x64 dot-matrix LCD with backlight
- Four AA batteries operation up to 6.5 hours (When recording, using the eneloop battery)
- Insert effects for input channels (2-band shelving EQ, compressor, exciter, de-esser)
- Mastering effects (2-band shelving EQ, multi-band compressor, normalize)
- Auto analysis mastering function
- 2-band shelving EQ for each track
- Reverb effects (Hall1/2,Room,Studio,Plate1/2)
- Optional AC adapter ready (TASCAM PS-P520)
- Can connect an external battery pack (TASCAM BP-6AA)
- Direct locate function by jog-wheel
- Repeat playback between IN/OUT point
- Track edit functions (COPY PASTE, COPY INSERT, MOVE PASTE, MOVE INSERT, OPEN, CUT, SILENCE, CLONE TRACK, CLEAN OUT)
- Bounce function allows recording of more six tracks
- UNDO/REDO(UNDO HISTORY) function
- Chromatic tuner and metronome included
- High-speed data transfer by USB2.0 connection
- Backup and restore songs
- File import/export by Wav format (mono/stereo)
- Export stereo master file as stereo wav format
- 4GB SD card included