# Atlona AT-HDMI-38 3x8 Atlona HDMI Switch/Splitter

### 3x8 Atlona HDMI Switch/Splitter. Model: AT-HDMI-38

The Atlona AT-HDMI-38 is a high performance 3-in 8-out HDMI Switcher with remote control. It allows you to connect up to 3 HDMI sources and output to 8 HDMI displays. The 8 HDMI outputs are identical, and each supports up to 1080p. All the outputs on the switch are mirrored, which means that same signal would be shown on all of the 8 monitors connected. Simply pressing one button on the remote you can select your desired HDMI source for display on eight HDMI TV&39;s simultaneously. This unit can be integrated with and controlled by most automation systems, such as Crestron AMX ect., through the RS-232 port.

### **Key Features:**

- High Resolution up to 1080p
- Splits 3 HDMI sources to as many as 8 outputs without signal loss.
- HDCP Compliant
- · Built-in EDID simulator and HDCP keyset allows each output to work independently in connecting to a HDMI display.
- Supports a wide range of PC and HDTV resolutions from VGA to UXGA and 480p to 1080p. Maximum resolution bandwidth is 165MHz.
- Provides multi-channel I2S digital audio output, with sampling rate up to 192KHz.
- Support both compressed and uncompressed multi-channel audio.
- Remote control
- RS232 Port

## **Technical Specifications:**

Bandwidth: 1.65GbpsResolutions: up to 1080p

Inputs: 3 x HDMIOutputs: 8 x HDMIRS232 port: 9-pinOutputs Type: Mirrored

• Power Supply: 5V (universal 110/220v)

• Dimensions: 17.17(W) x 4.5(D) x 1.73(H) - (inch)

• Weight: 6LB

### **Package Includes:**

- One AT-HDMI-38
- One Power Supply
- One IR Remote Control
- One User manual

## Warranty:

3 year manufacture warranty (parts&labor)