

SECO-LARM ST-2406-7AQ Power Supply/Charger/7.0A Continuous/7.5A Peak

Power Supply/Charger, 7.0A Continuous, 7.5A Peak

Features

- Selectable (6, 12, 24 VDC) voltage output
- Regulated and filtered output voltage
- Short circuit protection
- Thermal protection and compensation
- Built-in backup battery charger
- Switches to backup battery automatically in case of power loss
- Fused protection for battery charger
- 2 LEDs to indicate AC power input and DC power output status
- Compatible with lead acid or gel-type rechargeable battery
- Reverse polarity protected
- Low operating temperature
- Battery leads and foam tape included
- Compact design