

Shinybow SB-5470-b 4x2 Component Video HDTV Matrix Switcher/Splitter

The SB-5470 is a 4x2 Matrix Switcher that switches 4 Inputs Component (YPbPr), and Left & Right Analog Audio with IR remote. SB-5470 is a rugged 4x2 switcher, offering flawless and seamless switching and crystal-clear distribution of all HDTV video formats as well as audio signals. SB-5470 accepts up to four different input sources and you can seamlessly switch (select) any of these inputs to drive 2 outputs, without any signal degradation. It is universally compatible with all HDTV formats: 480i, 576i, 480p, 576p, 1080i, 720p and 1080p.

SB-5470 is a versatile and compact State of the Art switcher of choice when you need high-quality and reliable switching. The Switch can be controlled by its front-panel manual control button, or IR remote, and convenient front-panel LED's indicate which input has been selected for both outputs.

Features:

- Inputs: 4 x Component Video (YPbPr), 4 x Stereo Audio input
- Outputs: 2 x Component Video (YPbPr), 2 x Stereo Audio Outputs
- Switch easily between any four Component Video sources
- Maintains 480i, 480p, 576P, 720p, 1080i and 1080p resolutions
- Discrete IR remote (included)
- Easy to install and simple to operate
- Also can be used for Composite Video switching (will not do conversion between Component or Composite).

Specifications:

- Video Amplifier Bandwidth: 200 MHz
- Maximum Resolution : 1080p
- Input:
 - 4 Component Video (RGB, YPbPr)
 - 4 Left & Right Audio (RCA-Phono)
- Output:
 - 2 Component Video (RGB, YPbPr)
 - 2 Left & Right Audio (RCA-Phono)
- Power Consumption: 12VDC .66mA
- Switcher Size: (WxDxH) 9.25 x 5.5 x 1.73 inches

Package Includes:

- SB-5470 Matrix Routing Switcher
- Users Guide
- AC/DC Adapter: 12VDC, 500mA
- 1each 5RCA Component Video + L&R Audio Cable
- Wireless Remote Control w/batteries

Warranty: 1 year labor/parts manufacturers warranty.