

# TASCAM BO-32DE 32 Channel Euroblock to D-Sub Input Adaptor for Professional Installations

The TASCAM BO-32DE is a rugged, rackmounted audio adaptor designed for professional installation. 32 front-panel Euroblock connectors are internally bridged to four D-Sub output connectors on the rear panel, providing fast and easy I/O and interconnectivity between CD players, Digital Audio players, Mic Preamps, Zone Mixers, Distribution Amplifiers Audio over IP Convertors and more.

## **32 channels from 25-pin D-sub connectors can be transmitted to Euroblock terminals**

Euroblock terminals are the same for both input and output, so the 32 channels can be assigned freely as inputs or outputs in each 8 channel. The numbers of inputs and outputs can be set flexibly according to the needs of the system. For example, the unit could be set to have all 32 channels as inputs, 24 channels as inputs and 8 as outputs, or 16 channels each of inputs and outputs.

## **Included Euroblock plugs have tabs and cable band kit**

The included Euroblock plugs have tabs. Attaching the signal wires with wire bands minimizes stress on them during connection and disconnection.

## **Rackmount ears can be attached forward or backward allowing you to install the unit freely Rackmount ears can also be removed**

The unit can be mounted in a rack facing forward or backward by changing the direction that the rack-mount ears are attached to it. The rackmount ears can also be removed when using the unit placed on a tabletop.

## **Compact 1U size with a depth of 45 mm**

Thanks to the compact size, including a depth of only 45 mm, this breakout box can even be mounted in the back of a rack case.