

# Galaxy Audio AS-950 Wireless In-Ear Personal Monitor (Transmitter/Receiver) Kit/50Hz-15kHz

The AS-950 Wireless Personal Monitor system offers reliable quality and exceptional value. The receiver features a 50mW x 2 output with RF and stereo indicator. The transmitter features L/R level display, channel LCD display with channel up and down select, stereo XLR / 1/4" inputs and a headphone output with volume control. The AS-950 also offers 16 selectable UHF frequencies. EB4 ear buds feature titanium drivers, extended bass response, aluminum, alloy construction and now come standard with all WPM models.

## Features

- 16 Selectable UHF Frequencies
- Stereo or Mono Transmission
- Multiple Receivers can be used with 1 Transmitter
- Single/Dual Rack Mount Included
- 200' Range
- EB4 Ear Buds Included

An unlimited number of receivers may be added at any time.

## AS-950T Transmitter

- 16 Selectable UHF Frequencies
- AF L/R Indicator
- Transmits in Stereo or Mono
- Channel LCD Display
- Up/Down Channel Select
- XLR/1/4" Combo Input
- RF Output 10mW
- Detachable 1/2 Wave BNC Antenna Included

## AS-950R Receiver

- Built-in Limiter
- 50mW x 2 Earphone Out w/ Volume Control
- Channel LCD Display
- Up/Down Channel Select
- Operates on 2 AA Batteries (Alkaline or Rechargeable)
- 3.35 oz (95 g)