

Shinybow SB-3776 BNC 1x2 Component Video(BNC) Splitter

The SB-3776BNC is a 1 input to 2 output Component Video Distribution Amplifier. They are used to distribute video signals to multiple destinations, These products provide multiple outputs that are identical to the source signal. There are useful for distributing signals from VCRs, Camcorders, Video Game Consoles, DVDs, Satellite Receivers, CATV Set Top Boxes, etc.

Features

- INPUT: 1x Component Video
- OUTPUT: 2x Component Video
- High resolution Support HDTV 480p, 720p, 1080i60, 1080P
- Lighted On/Off Power Switch
- Video Bandwidth >300 Mhz
- Accepts NTSC and PAL
- Regulatory Approvals CE, FCC, RoHS(2002/95/EC)

Specifications

- Type of Amplifier: 1:2 Component VideoDistribution Amplifier
- Input:
 - Video x 1: Component (BNC) (YPbPr/YCbCr/RGB) Video 75 Ohms
- Output:
 - Video x 2: Component Video (BNC) (YPbPr/YCbCr/RGB)
- Video Bandwidth: 300MHz
- Enclosure type: Metal case
- Power Consumed: 420mA Maximum
- Power Source: DC 12 Volts, @500mA
- Size(L,W,H): 12 in x 6.4 in x1.55 in

Package Includes:

- SB-3776BNC Distribution Amplifier
- Users Guide
- AC/DC Adapter: 12VDC, 500mA