

Atlona AT-SAV18 1x8 S-Video and Audio Distribution Amplifier

Atlona 1x8 S-Video and Audio Distribution Amplifier. Model: AT-SAV18

The Atlona AT-SAV18 is a commercial quality S-Video with Stereo Audio signal distribution amplifier. This 1x8 S-Video with Stereo Audio Distribution Amplifier is a perfect solution for anyone who needs to send one source of composite video with Audio to multiple displays at the same time. With 1 x S-Video/Audio Input and 8 x S-Video/Audio Outputs, the AT-SAV18 is capable of sending signal from one source to all 8 desired displays at the same time without signal degradation. This unit is perfect for applications for distributing signals from VCRs, Camcorders, Video Game Consoles, DVDs, Satellite Receivers, Set Top Boxes, etc.

Key Features:

- High Video and Audio Signal Bandwidth allows users to use extra long cables and still have a great quality image without signal degradation
- Buffered Input also allows users to use an extra long input cable
- Gold plated S-Video and RCA jacks
- Supports Pal and NTSC signals
- Standard 19-inch Rack Mount Size - 1U (rack ears are included)

Specifications:

- Video Bandwidth: 1000Mhz (1 GHz)
- Inputs: 1 x S- Video and Stereo Audio (1 x 5pin (Y/C) and 2 x RCA females)
- Outputs: 8 x S-Video and Stereo Audio (1 x 5pin (Y/C) and 2 x RCA females each output)
- Video Inputs/Outputs: 75 Ohm
- Audio Inputs/Outputs: 47 Ohm
- Input DDC Signal: 12v 500mA (Universal Power Supply 110v/240v)
- Dimensions (L x W x H): 9.2 x 5.7 x 1.6 (inch)
- Rack-Mountable: 1U
- Shipping Weight: 5 lbs

Package Includes:

- AT-SAV18 Distribution Amplifier
- Instruction Manual
- Universal AC Adaptor : 12V DC
- Rack Mount Ears (Pair)

Warranty:

- 3 year parts and labor